



# Electric Log Lithium Battery

ELI-BATTERY



**OPERATION INSTRUCTIONS**

# IMPORTANT INSTRUCTIONS

1. The battery should be stored in a cool, dry, indoor location, avoiding rain and outside elements.
2. Do not keep the battery in a low voltage state for a prolonged amount of time. In periods of no use or low use, it is suggested to charge every three months.
3. Do not immerse the battery in water or make it wet.
4. Do not modify or disassemble the battery.
5. Do not put the battery into fire.
6. Please use the correct charger to charge the battery.
7. If the liquid of the battery gets into your eyes, do not rub your eyes, rinse with water and consult doctors immediately.
8. If there is any malfunction at the time of charging, please contact your dealer.

## POWER DATA

Size(inch)	1 1/2 x 3 1/8 x 5 3/8
Weight(ounce)	18
12V Capacity(mAh)	22,500 (with 3.7V)
Input	12.6V 3A
Output	12V 3A
Spec. of charger	12V 2A
Charge Time	~4hrs
Operating Temperature	-4~140 Fahrenheit
Battery Gauge	Yes

## BOX CONTENTS



Battery



Male-Male  
power cable

## OPERATION



1. Power Input
2. Power Output
3. Battery Gauge
4. Power Switch

To use the Sunset Series logset with the Electric Log Lithium Battery, simply plug in the power cable from the output on the battery to the Sunset Series logset (this will replace the AC connection at the logset.) Once plugged in, turn on the power switch and the Sunset Series logset will be operating off of battery power.

To charge the Electric Log Lithium Battery simply use the AC connection from the Sunset Series logset power adapter and plug in to the input on the battery pack. The battery power switch must be switched on to charge. The charging indicator lights will show the amount of power in the battery. Once all indicator lights have turned green the battery is fully charged. This battery can be used to operate the Sunset Series logset while charging.

© 2018

MODERN  FLAMES

[www.modernflames.com](http://www.modernflames.com)

Please dispose of properly.

